

Growatt ShineMaster

- Local webserver for easy configuration
- Supports RS485, Ethernet, 4G communication
- Up to 64 inverters connection
- Multi-function and high performance



P O W E R
- I N G O
T O M O -
R R O W O

GROWATT

www.ginverter.com

Datasheet	ShineMaster	ShineMaster4G
Hardware Parameter		
Power adapter	Input: 100-240V, 50/60Hz AC Output 5V(+/-15%), 1A DC	
Power consumption	2.5W	
Application Parameters		
Max.inverters connection	32	64
Max. communication range	500m	
Communication with inverters	RS485 (Modbus RTU protocol)	
Communication with server	TCP(Modbus TCP protocol)	
Support network	Ethernet	4G
Data transmission interval	5 Minutes	
Default server URL	server.growatt.com	
Supported servers	ShineServer	
General Data		
Dimensions(W/H/D)	130/84/25mm	
Weight	180g	
Language	English	
Mounting options	Wall-mounted	
Ambient temperature range	-30°C ~ +60°C	
Degree of protection	IP30	
Warranty	1 year	
CE		



The logo for SOLSOL features the word 'SOLSOL' in a bold, blue, sans-serif font. The letter 'O' in the first 'SOLSOL' is replaced by a blue circle containing a white plus sign (+), and the letter 'O' in the second 'SOLSOL' is replaced by a blue circle containing a white minus sign (-).

SOLSOL s.r.o.
 Králova 298/4, Brno 616 00, Czech Republic
 sales@solsol.cz
 www.solsol.cz